

Moving Test – MT680s

Single-phase Test System with
Integrated Current Source



Accuracy Class 0.1

General

The state of the art test system MT680s consists of a class 0.1 reference meter with built-in current source (up to 120 A). The system is particularly designed for analysis of complete metering installations and local mains conditions.

The equipment offers high functionality combined with an excellent menu guided operation via colored 6.5" touch screen or externally via interface.



Alphanumeric keypad

Features

- Accuracy class 0.1
- Direct measurement up to 120 A and 500 V
- Calibration under real load conditions
- Verification of the energy registration
- 4 quadrant measurement
- Harmonic spectrum analysis
- Wave form analysis

Functions

- Testing meter installations in two-wire systems
- Power and energy measurements for active, reactive and apparent power
- Measuring frequency, phase shift and power factor
- Harmonic spectrum analysis for voltage and current up to the 40th order
- Measuring the distortion factor
- Vector representation of the measuring values
- Oscilloscope function for curve scanning
- Energy dosing with built-in current source



6.5" Touch screen

Data Management

For later download on a PC, the operator can store all test results and measuring values on especially configured USB stick. The data management software MTVis provides the ability to transfer the data between MT680s and an external PC.

All test results can be summarized and printed in a test report.




MT680s suitcase

Single-phase meter

Temperature Sensor MT3450 (optional)

The temperature sensor MT3450 can be used with the devices of the MT-series. It serves for temperature registration on-site. The temperature will be indicated on the MT-display and will be recorded every time data are stored.

Stackable Sub-D plug



Temperature sensor

Actual Values Measurement

All instantaneous values are displayed simultaneously in a summary:


- RMS values of voltage and current
- Phase angle between voltage and current
- Active, reactive and apparent power
- Test frequency
- Power factor ($\cos \varphi$)



Vector Display

The colored vector diagram display for voltage and current makes it very easy to detect wiring faults in voltage and current circuits.

All measured values can be stored on USB stick according to the customer information data.




Error Measurement

By entering all relevant test parameters, like meter constant and the number of pulses, the system can perform the error measurement on electricity meters. The percentage error including all statistical values can be stored according to the customer information data. In order to inform the operator about the status of the measurement a bar graph indicates continuously the measured energy as well as the detected metrology pulses from the unit under test.



Automatic Operation

By using predefined test routines the MT680s system can operate automatically without need of an external PC.



Harmonic Measurement

Due to the high sampling rate of the working standard the MT680s is able to measure harmonics in voltage and current up to the 40th THD (conform to the voltage quality norm DIN EN 50160). The measured harmonic spectrum can be displayed in a chart or in a logarithmic diagram.



MT680s Single-phase Test System

General

| | |
|------------------------------------|----------------------------|
| Power supply | 85 ... 265 V, 47 ... 63 Hz |
| Power consumption | max. 135 VA |
| Temperature range, operation | -10° ... + 50° C |
| Temperature range, storage | -15° ... + 65° C |
| Relative humidity (not condensing) | max. 95 % |
| Dimensions (DxWxH) | 248 x 300 x 196,2 mm |
| Weight | ~ 8.4 kg |

Safety

| | |
|--|------------------------------|
| IP class according to DIN EN 60529 | IP30 |
| Declaration of conformity | CE conform |
| Protection class according to DIN EN 61140 | I |
| Overvoltage category voltage measurement | CAT III 300 V / CAT II 600 V |
| Overvoltage category current measurement | CAT III 300 V / CAT II 600 V |

Reference meter

| | |
|--|---------------------------|
| Measuring modes | 2WA / 2WR / 2WAP |
| Fundamental frequency | 45 ... 65 Hz |
| Bandwidth | 3000 Hz |
| Sampling | 16 bit 504 samples/period |
| Accuracy class for measuring of power / energy | 0.1 |
| Angle measurement accuracy 3) 4) | < 0.015° |
| Frequency measurement deviation | ± 0.01 Hz |

Voltage Measurement

| | |
|---|---|
| Voltage measurement | 5 mV ... 500 V |
| Voltage range(s) | 250 mV, 5 V, 60 V, 125 V, 250 V, 420 V |
| Voltage measurement accuracy 5) | < 0.05 % @ 30 V ... 500 V < 1 % @ 50 mV ... < 30 V < 3 % @ 5 mV ... < 50 mV |
| Voltage measurement temperature drift 3) | < 15 x 10 E-6 / K |
| Voltage measurement stability 1) 3) | < 60 x 10 E-6 |
| Voltage measurement long term stability 2) 3) | < 100 x 10 E-6 / Year |

Current measurement

| | |
|---|---|
| Current measurement | 1 mA ... 120 A |
| Current range(s) | 100 A, 50 A, 20 A, 10 A, 5 A, 2 A, 1 A, 500 mA, 200 mA, 100 mA, 50 mA, 20 mA |
| Current measurement accuracy 5) | < 0.05 % @ 10 mA ... 120 A < 0.2 % @ 5 mA ... < 10 mA |
| Current measurement temperature drift 4) | < 20 x 10 E-6 / K |
| Current measurement stability 1) 4) | < 70 x 10 E-6 |
| Current measurement long term stability 2) 4) | < 100 x 10 E-6 / Year |

Power Measurement

| | |
|---|--|
| Power/energy measurement accuracy 3) 6) | < 0.1 % @ 10 mA ... 120 A < 0.25 % @ 5 mA ... < 10 mA |
| Power/energy measurement temperature drift 3) 4) | < 35 x 10 E-6 / K |
| Power/energy measurement stability 1) 3) 4) | < 100 x 10 E-6 |
| Power/energy measurement long term stability 2) 3) 4) | < 200 x 10 E-6 / Year |

Source

| | |
|--------------------------------|---|
| Current min. max. | 1 mA ... 120 A |
| Current range(s) | 100 A, 50 A, 20 A, 10 A, 5 A, 2 A, 1 A, 500 mA, 200 mA, 100 mA, 50 mA, 20 mA |
| Current max. voltage per range | 600 mV (100 A .. 20 A), 2.0 V (10 A), 4.0 V (5 A) 8.0 V (2 A .. 20 mA) |
| Current max. output power 8) | 60 VA |
| Current accuracy 4) | < 0.1 % |
| Current distortion 4) | < 0.5 % |
| Frequency range | 45 ... 65 Hz |
| Phase angle setting range | 0.00 ... 359.99° |
| Phase angle stability 4) 9) | < 0.15 ° |

- 1: Stability over 1 hour (every minute one measurement with $t_i = 60$ s)
 2: Stability over 1 year (every month one measurement over one hour)
 3: From 30 V ... 500 V
 4: From 10 mA ... 120 A
 5: Related to the read value at optimum range selection
 6: Related of apparent power
 7: of range 30 % ... 120 %
 8: Related of end of maximum range and end of range and ohmic load
 9: Stability over 1 hour (measurement with $t_i = 10$ s)

13.012016

Subjects to alteration.